



ERICSSON SPR1200 MULTI-SCREEN STREAM PROCESSOR



The Ericsson SPR1200 is a high density adaptive bit-rate (ABR) stream processor for operators to launch television services in the multi-screen environment. It will deliver services to multiple internet connected devices simultaneously, including connected TVs, notepads and mobile phones.

Each Ericsson SPR1200 can be configured in a high input or high output mode. In the high input mode it can transcode 12 services, each into up to 8 output profiles. In the high output mode it can transcode 6 services, each into up to 24 output profiles.

The Ericsson SPR1200 and Ericsson NPR1200 work in unison to deliver services over the internet. The Ericsson SPR1200 transcodes many video and audio services into multiple synchronised profiles, then the Ericsson NPR1200 segments the profiles and wraps the packets to be sent over the internet.

The SPR1200 is designed for high availability, and offers a hot-standby spare running as automatic 1+1 mirrored units to ensure maximum reliability and service up-time. An advanced web-based user interface allows easy configuration, without the need for an external control system.

PRODUCT OVERVIEW

Multi-screen Delivery

High density adaptive bit rate video processing for delivering services over the internet to multiple devices simultaneously .

Flexible Transcoding

The Ericsson SPR1200 will transcode from MPEG-2, MPEG-4 AVC, SD and HD, to MPEG-4 SD and HD for ABR.

High Density Processing

Class leading density of multiple ABR transcodes for up to 12 services in a 1RU chassis. Solves the scaling problem to deliver more services to more devices.

“Pay As You Grow” Expansion

Only buy what you need today, the Ericsson SPR1200 can be expanded in the field with additional hot-swap Media Processing Modules and video transcoding licences.

Reliability to Keep You On Air

Chassis and PSU redundancy options, and hot swap modules maximise your on air time, and minimise off air interruptions.

BASE UNIT FEATURES

Ericsson SPR1200 Multi-screen Stream Processor

Standalone Configuration

- Single 1RU chassis

SPR12/CHASSIS/1AC, FAZ 101 0161/61

- Single AC power supply

SPR12/CHASSIS/2AC, FAZ 101 0161/62

- Dual AC power supplies

SPR12/CHASSIS/1DC, FAZ 101 0161/63

- Single DC power supply

SPR12/CHASSIS/2DC, FAZ 101 0161/64

- Dual DC power supplies

Redundant Pair 1+1 configuration

- Pair of units for 1+1 mirrored hot-standby redundancy

SPR12/CHASSIS/1AC/RAS, FAZ 101 0161/71

- Each unit has a single AC power supply

SPR12/CHASSIS/2AC/RAS, FAZ 101 0161/72

- Each unit has dual AC power supplies

SPR12/CHASSIS/1DC/RAS, FAZ 101 0161/73

- Each unit has a single DC power supply

SPR12/CHASSIS/2DC/RAS, FAZ 101 0161/74

- Each unit has dual DC power supplies

BASE UNIT FEATURES cont.

Base Chassis Functionality includes:

- Control via 2x Electrical Ethernet (100/1000BaseT)
- Data i/o via 4x Electrical Ethernet (100/1000BaseT)
- 1 Gbps duplex communication to each module
- License Key Server to enable software licenses on the chassis

Platform Processing Capacities

- Up to six Media Processor Modules (MPM) in chassis with single power supply
- Up to four modules in chassis with dual power supplies
- Up to two services (transcoded to multiple output profiles) per module
- Support for multiple audio tracks per service (including languages, codecs and bitrates)
- Audio Leveling Control for reducing audio level differences within a service
- A generally-available set of resolutions is backed-up by support for custom resolutions

HARDWARE / SOFTWARE OPTIONS

Media Processor Module

SPR/HWO/MPM12, FAZ 101 0161/107

SPR/HWO/MPM12/R, FAZ 101 0161/108

- IP video input, via data interface on chassis
- Support for Closed Captions pass through

Full HD Profile License

SPR/SWO/ABR/fullHD, FAZ 101 0161/97

SPR/SWO/ABR/fullHD/R, FAZ 101 0161/103

- License can be used for any resolution ABR profile
- Up to 3 full HD video transcodes per module, 18 per chassis
- Requires full HD input: HD, MPEG-4/MPEG-2

Half HD Profile License

SPR/SWO/ABR/halfHD, FAZ 101 0161/98

SPR/SWO/ABR/halfHD/R, FAZ 101 0161/104

- License for output profiles up to 720 p 25/30
- License can also be used for SD or sub SD profiles
- Up to 12 half HD video transcodes per module, 72 per chassis
- Requires an HD input: HD, MPEG-4/MPEG-2

SD Profile License

SPR/SWO/ABR/SD, FAZ 101 0161/99

SPR/SWO/ABR/SD/R, FAZ 101 0161/105

- License for output profiles up to 480p 25/30
- License can also be used for sub SD profiles
- Up to 24 SD video transcodes per module, 144 per chassis
- Any input: HD/SD, MPEG-4/MPEG-2

Sub SD Profile License

SPR/SWO/ABR/subSD, FAZ 101 0161/100

SPR/SWO/ABR/subSD/R, FAZ 101 0161/106

- License for output profiles up to 359p 25/30
- Up to 24 SD video transcodes per module, 144 per chassis
- Any input: HD/SD, MPEG-4/MPEG-2

ERICSSON SPR1200 MULTI-SCREEN STREAM PROCESSOR

MPEG-1 & MPEG-2 Layer II Audio License

SPR/SWO/AUD/MP2, FAZ 101 0161/18

SPR/SWO/AUD/MP2/R, FAZ 101 0161/26

- Multiple audio transcodes per video service, depending on system configuration

AAC Audio License

SPR/SWO/AUD/AAC, FAZ 101 0161/19

SPR/SWO/AUD/AAC/R, FAZ 101 0161/27

- Multiple audio transcodes per video service, depending on system configuration

Dolby® Digital (AC-3) Audio License

SPR/SWO/AUD/AC3, FAZ 101 0161/20

SPR/SWO/AUD/AC3/R, FAZ 101 0161/28

- Multiple audio transcodes per video service, depending on system configuration

Dolby® Digital Plus (E-AC-3) Audio License

SPR/SWO/AUD/EAC3, FAZ 101 0161/120

SPR/SWO/AUD/EAC3/R, FAZ 101 0161/123

- Multiple audio transcodes per video service, depending on system configuration

Dolby® Digital (AC-3) Decode License

SPR/SWO/AUD/AC3DEC, FAZ 101 0161/95

SPR/SWO/AUD/AC3DEC/R, FAZ 101 0161/101

- Up to 1 audio decode per video service

Audio Levelling Control License

SPR/SWO/ALC/C, FAZ 101 0161/111

SPR/SWO/ALC/F, FAZ 101 0161/112

SPR/SWO/ALC/C/R, FAZ 101 0161/113

SPR/SWO/ALC/F/R, FAZ 101 0161/114

- License audio levelling control on one stereo pair
- First 12 stereo pairs per chassis are charged; remainder per chassis are free

SPECIFICATIONS

Media Processor Module

Up to six Media Processor Modules per chassis
Module level hot swap

Module Inputs and Outputs

Video & Audio

All video and audio services are input and output via transport streams via the data Ethernet ports

HD Video Decode

Supports Video Resolutions (HD):

1080i x 1920 / 1440 / 1280 @ 25 fps
1080i x 1920 / 1440 / 1280 @ 29.97 fps
720p x 1280 / 960 @ 50 fps
720p x 1280 / 960 @ 59.94 fps

Bit-rates (HD):

MPEG-2: MP@HL 0.5 Mbps to 30 Mbps
MPEG-4: HP@L4.0-L4.1 0.5 Mbps to 25 Mbps

SD Video Decode

Supports Video Resolutions (SD):

576i x 720 / 704 / 640 / 544 / 528 / 480 / 352 @ 25 fps
480i x 720 / 704 / 640 / 544 / 528 / 480 / 352 @ 29.97 fps

Bit-rates (SD):

MPEG-2: MP@ML 0.256 Mbps to 15 Mbps
MPEG-4: MP@L3-L4.1 0.256 Mbps to 12 Mbps

Audio Decode

MPEG-1 & MPEG-2 Layer II audio (mono, stereo, dual-mono)
Bit-rate: 32-384 Kbps

AAC-LC & HE-AAC (stereo, 5.1)
Bit-rate: stereo: 64-192 Kbps (AAC-LC),
32-128 Kbps (HE-AAC)
5.1 Surround Sound: 160-512 Kbps (AAC-LC),
128-192 Kbps (HE-AAC)

Dolby® Digital (AC3)
Bit-rate: 56-640 Kbps (mono, stereo)
224-640 Kbps (5.1)

Video Encode

CBR rate control
Progressive encoding only

Applies to

SPR/SWO/ABR/fullHD, FAZ 101 0161/97

Supports Video Resolutions (full HD):

1920 x 1080p @ 25 / 29.97 fps
1280 x 720p @ 50 / 59.94 fps

SPR/SWO/ABR/halfHD, FAZ 101 0161/98

Supports Video Resolutions (half HD):

1280 x 720p @ 25 / 29.97 fps
1024 x 576p @ 25 / 29.97 fps
960 x 540p @ 25 / 29.97 fps

Bit-rates * (HD):

full HD: 2.8 Mbps to 25 Mbps
half HD: 0.8 Mbps to 25 Mbps

Applies to

SPR/SWO/ABR/SD, FAZ 101 0161/99 &

Supports Video Resolutions (SD):

16:9 - 854 x 480p, 704 x 396p, 640 x 360p @ 25 / 29.97 fps
4:3 - 640 x 480p, 544 x 408p, 480 x 360p @ 25 / 29.97 fps

Broadcast - 704 x 480p, 704 x 576p (576p not possible if source is 480i)

SPR/SWO/ABR/subSD, FAZ 101 0161/100

Supports Video Resolutions (subSD):

16:9 - 544 x 306p, 480 x 270p, 416 x 234p, 320 x 180p @ 25 / 29.97 fps
4:3 - 400 x 300p, 320 x 240p @ 25 / 29.97 fps

Bit-rates * (SD):

SD: 0.27 Mbps to 20 Mbps
sub SD: 0.1 Mbps to 20 Mbps

* At full frame rate. Dependant on resolution, profile & level.

Audio Encode

MPEG-1 & MPEG-2 Layer II audio (mono, stereo, dual-mono)
Bit-rate: 32-384 Kbps

AAC, AAC-LC & HE-AAC (stereo, 5.1)
Bit-rate: stereo 64-192 Kbps ((LC),
32-128 Kbps (HE)
5.1 Surround Sound: 160-512 Kbps (LC),
128-192 Kbps (HE)

Dolby® Digital (AC3)
Bit-rate: 56-640 Kbps (mono, stereo),
224-640 Kbps (5.1)

Dolby® Digital Plus (E-AC3)
Bit-rate: 32-56 Kbps (mono)
64-640 Kbps (mono, stereo)
192-640 Kbps (5.1)

Multiple audio transcodes per input video service

VBI

Closed captioning EIA-608, EIA-708 and SCTE 20

Output Interfacing

Output

4x Electrical Ethernet (10/100/1000BaseT)

Management

2x Electrical Ethernet (10/100/1000BaseT)

SNMP v1/v2 for alarm traps

User management via web browser and XML

IP v4

nCompass Control by Ericsson for monitoring alarms

IGMP v1/v2/v3

Physical and Power

Dimensions (H x W x D)

4.45 x 44.20 x 59.69 cm (1.75 x 17.40 x 23.50 inches)

Weight

7.3 kg (16 lbs) with a single PSU
8.3 kg (18.3 lbs) with a dual PSU
0.33 kg (0.73 lbs) per module

Input Voltage

100 VAC to 240 VAC, 50/60 Hz

Power Consumption

Chassis only 40 Watt
MPM 40 Watt
Up to 300W depending on modules fitted

Environmental Conditions

Operating Temperature

-10°C to +50°C (14°F to 122°F)

Storage Temperature

-40°C to +85°C (-40°F to 185°F)

Relative Operating Humidity

10% to 90% (non-condensing)

Compliance

CE marked in accordance with EU Low Voltage and EMC Directives

EMC Compliance

EN55022, EN55024, AS/NZS3548, EN61000-3-2, EN61000-3-3 and FCC CFR47 Part 15B Class A

Safety Compliance

EN60950-1, IEC60950-1, UL60950-1 and NRTL listed